

→ 简介

K

■ 1oo2

■

■

■

■

-

→ 技术参数

24V AC/DC

0.85~1.1

50Hz~60Hz

≤2.2 W/24V DC ≤5.4 VA/24V AC

≤50mA/24V DC

≤15Ω

2~20kΩ

3NO+1NC 2NO+2NC

AgSnO₂+0.2μmAu

AC-15 5A/230V DC-13 5A/24V

10A gL/gG(NO) 6A gL/gG(NC)

数

≤100ms

≤30ms ≤100ms

≤30ms ≤100ms

20ms

境 数

IEC/EN 60947 IEC 61326-3-1

IEC/EN 61000-6-2 IEC/EN 61000-6-4

250V AC

6000V (1.2/50μs)

QR Code

K

Nanjing New Power Electric Co., Ltd.

: <http://www.anpe.cn>

: 025-84459479

→ 简介

K

■ 1oo2

■

■

■

■

-

→ 技术参数

24V AC/DC

0.85~1.1

50Hz~60Hz

≤2.2 W/24V DC ≤5.4 VA/24V AC

≤50mA/24V DC

≤15Ω

2~20kΩ

3NO+1NC 2NO+2NC

AgSnO₂+0.2μmAu

AC-15 5A/230V DC-13 5A/24V

10A gL/gG(NO) 6A gL/gG(NC)

数

≤100ms

≤30ms ≤100ms

≤30ms ≤100ms

20ms

境 数

IEC/EN 60947 IEC 61326-3-1

IEC/EN 61000-6-2 IEC/EN 61000-6-4

250V AC

6000V (1.2/50μs)


警告!



()

1 / 3

产品型号	输入设备	复位方式	触点数量
NPFSR-K4F31AMD		/	3NO+1NC
NPFSR-K4F31MD			3NO+1NC
NPFSR-K4F22AMD		/	2NO+2NC
NPFSR-K4F22MD			2NO+2NC
NPFSR-K4C31AD		/ /	3NO+1NC
NPFSR-K4C22AD		/ /	2NO+2NC



NPFSR-K4F31AMD

NPFSR-K4F22AMD

:

: 211500



警告!

